

<b>Model Name</b>	<b>SE-500</b>
<b>Product Name</b>	<b>SD 4-Channel Digital Video Switcher</b>
<b>Video Standard</b>	SD
<b>Video Format</b>	NTSC 480i 59.94Hz PAL 576i 50Hz
<b>Video Processing</b>	SDI: 4:2:2
<b>Input Routable / Crosspoint</b>	Fixed
<b>Video Input</b>	4x CV or 4x Y/C
<b>Mix HD &amp; SD source</b>	N/A
<b>Computer Graphic Interface</b>	N/A
<b>Video output</b>	2x CV & 1x Y/C or 1x CV & 1x YUV 1x CV Quad PVW
<b>Down-converted output</b>	N/A
<b>Built-in Multi-view monitoring out</b>	1x CV
<b>Audio input</b>	2x ¼" Mic jack 2x Unbalanced RCA (pair)
<b>Audio output</b>	2x Unbalanced RCA (pair)
<b>Embedded audio support</b>	N/A
<b>Audio Delay Calibration</b>	N/A
<b>A+V switching</b>	N/A
<b>Chromakey</b>	N/A
<b>Title Creator</b>	N/A
<b>USK</b>	N/A
<b>DSK</b>	N/A
<b>Picture in Picture</b>	1
<b>Logo Insertion</b>	N/A
<b>Still Store</b>	N/A
<b>Effects</b>	Quad, Split, 11 Wipe with border
<b>Transition Preview</b>	Yes
<b>Sync / Reference In/Out</b>	Built-in Genlock (internal)

<b>Tally Output</b>	1x D-sub 15pin, dual color
<b>PC Remote Control</b>	Via RS-232
<b>Built-in Audio Mixer</b>	3 channels
<b>Special Features</b>	N/A
<b>Chassis</b>	Unibody
<b>Power</b>	DC 12V 18W
<b>Accessory</b>	CB-46/47/50 (30/50/100m)